

PRODUCT

Single user wrist strap and bench continuous monitor

This device is used to ensure that the user's wrist strap is functioning correctly.

If a malfunction is found, the unit will signal the fault giving both visual and audible alarms identifying the failing item.

Plug and play compatible with most standard wrist straps.



Front



Back

FEATURES

- Audible and visual alarms
- Compatible with most single wire wrist straps
- Easy to use: Plug and play
- Factory calibrated

PRODUCT CODE	DESCRIPTION	DIMENSIONS	QUANTITY
093-1016	Single user wrist strap and bench continuous monitor	H 1.125" x W 4.00" x D 2.25"	1

To request a quotation or for more information, please call **+44 (0)1473 836200**
email info@antistat.co.uk or visit www.antistat.co.uk

IMPORTANT: This data sheet and its contents (the "Information") belong to Antistat or are licensed to it. No licence is granted for the use of it other than for information purposes in connection with the products to which it relates. No licence of any intellectual property rights is granted. The Information is subject to change without notice and replaces all data sheets previously supplied. The Information supplied is believed to be accurate but Antistat assumes no responsibility for its accuracy or completeness, any error in or omission from it or for any use made of it. Users of this data sheet should check for themselves the Information and the suitability of the products for their purpose and not make any assumptions based on information included or omitted. Liability for loss or damage resulting from any reliance on the Information or use of it (including liability resulting from negligence or where Antistat was aware of the possibility of such loss or damage arising) is excluded. © 2021 Antistat.

SPECIFICATION

DESCRIPTION	VALUE
Wrist open circuit voltage	0.7 VDC, +0.1VDC @ <2mA
Mat open circuit voltage	5.0 - 7.5 VDC
Alarm indicators	Alarm/LED (green: safe, red: unsafe)
Alarm set point	6.5 megohm
Audible alarm	10 beeps (max); 5 seconds
Monitoring capabilities	One wrist strap/person
Weight	7.4 oz
Power input	240v - 50Hz
Power output	12VDC, 200mA
Adjustment	No adjustments required

To request a quotation or for more information, please call **+44 (0)1473 836200**
 email info@antistat.co.uk or visit www.antistat.co.uk

IMPORTANT: This data sheet and its contents (the "Information") belong to Antistat or are licensed to it. No licence is granted for the use of it other than for information purposes in connection with the products to which it relates. No licence of any intellectual property rights is granted. The Information is subject to change without notice and replaces all data sheets previously supplied. The Information supplied is believed to be accurate but Antistat assumes no responsibility for its accuracy or completeness, any error in or omission from it or for any use made of it. Users of this data sheet should check for themselves the Information and the suitability of the products for their purpose and not make any assumptions based on information included or omitted. Liability for loss or damage resulting from any reliance on the Information or use of it (including liability resulting from negligence or where Antistat was aware of the possibility of such loss or damage arising) is excluded. © 2021 Antistat.